





Kompatibilitätsliste Dimmer

Kompatibel: kein Flackern,
keine Geräusche

Semi-kompatibel: kein
Flackern, ggf. Geräusche













Inkompatibel: ggf.
Flackern, ggf. Geräusche

| Dimmer brand | Type | Max. load | Spot RA HQ Dim | | Downlight HZ Dim | | | | Spot Ava | | Spot 3C Compact |
|--------------|-----------------------|------------------------|---|------|--|------|-----|-----|----------|---|---|
| | | | 7W | 8W | 7W | 10W | 13W | 16W | 7W | 9W | 12W |
| | | |  | |  | | | | |  |  |
| ABB | 2250 AJ-513 | 60 - 600W | | 2-11 | | | | | 2-6 | 2-6 | |
| Berker | 286610 | 20-500W | 1-13 | 1-5 | 1-13 | 1-10 | 1-7 | 1-6 | | 1-11 | |
| Berker | 2819 | 60-400W | | 1-10 | | | | | | | 1-9 |
| Berker | 2830 10 | 60-400W | 1-10 | | | 1-8 | 1-6 | 1-5 | 1-11 | | 1-9 |
| Bticino | L-N-NT4411N | 3-400W | 1-11 | 1-11 | 1-11 | 1-11 | 1-6 | 1-5 | | | 1-5 |
| BULL | B6GD100 | 500W | | | | 1-10 | 1-7 | 1-6 | 1-14 | | 1-13 |
| BUSCH-JAEGER | 6523U | LED typical 2 ... 100W | 1-13 | 1-11 | 1-13 | 1-10 | 1-7 | 1-6 | 1-14 | 1-11 | 1-7 |
| BUSCH-JAEGER | 6513 U-102 | 40 - 420W | 1-11 | 1-9 | 1-11 | 1-8 | | 1-5 | 1-12 | 1-9 | 1-11 |
| BUSCH-JAEGER | 2247U | 20 - 500W | | 1-11 | 1-13 | 1-10 | 1-7 | 1-6 | 1-14 | 1-6 | 1-11 |
| BUSCH-JAEGER | 6524U | LED 2 - 100 W | 1-13 | 2-5 | 1-13 | 1-10 | 1-7 | 1-6 | 1-14 | | |
| BUSCH-JAEGER | 2250U | 600W | 1-16 | 2-11 | 1-16 | 1-12 | 1-9 | 1-7 | 1-17 | 2-13 | 1-14 |
| BUSCH-JAEGER | 6591 U-101-500 | 420W | 1-13 | 1-12 | 1-11 | 1-11 | 1-7 | 1-6 | 1-12 | 1-10 | |
| BUSCH-JAEGER | 6523 UR-103 | 2-400W | 1-11 | 1-10 | 1-11 | 1-11 | 1-6 | 1-5 | 1-11 | 1-9 | |
| Busch | 6523U-102 | 10-250W/LED2-100W | 1-13 | | 1-13 | 1-10 | 1-7 | 1-6 | 1-14 | 1-11 | 1-9 |
| Busch | 6526U | 10-200W/LED2-100W | | | | | 1-7 | | | | |
| Eltako | EUD61NPN-UC | 400W | | 1-9 | | | | | | | |
| EFAPEL | 21215 | 3-50W | 1-6 | 1-6 | 1-6 | 1-5 | 1-3 | 1-3 | 1-7 | 1-5 | |
| EFAPEL | 21214 | 3-35W | 1-4 | 1-4 | 1-4 | 1-3 | 1-2 | 1-2 | 1-5 | 1-4 | 1-2 |
| EFAPEL | 21216 | 3-85W | 1-11 | 1-10 | 1-11 | 1-8 | 1-6 | 1-5 | 1-12 | 1-9 | |
| EPV | PAB 315 | 20-315W | 1-8 | 1-7 | 1-8 | 1-6 | 1-4 | 1-4 | 1-9 | 1-7 | 1-11 |
| Feller | 40200 LED FMI 61 | 4-200W/VA | 1-5 | 1-5 | 1-5 | 1-3 | 1-3 | 1-2 | | 1-5 | |
| Feller | 40600 RL FIM61 | 20-300W/VA | 1-8 | 1-7 | 1-7 | 1-5 | 1-4 | 1-3 | | 1-7 | 1-13 |
| Feller | 40300 RC FMI 61 | 40-600VA/W | 1-16 | 1-7 | | | | | 1-16 | 1-12 | 1-9 |
| Feller | 40600 RLC FMI 61 | 20-600VA/W | | 1-15 | 1-15 | 1-11 | 1-8 | 1-7 | | 1-12 | 1-13 |
| GIRA | UNIV 420WV | 50 VA - 420 VA | | 1-9 | | | | | | | |
| GIRA | HAL/LED 500VA | 20 VA - 500 VA | | | | | | | 1-6 | 1-6 | |
| GIRA | 117600/104 | 50-420W | 1-11 | | 1-11 | 1-8 | 1-6 | 1-5 | | | 1-13 |
| GIRA | 226200/101 | 20-500W/LED3-100W | 1-13 | | 1-13 | 1-10 | 1-7 | 1-6 | 1-14 | 1-11 | 1-8 |
| GIRA | 0302 00/101 | 60-600W | 1-16 | | 1-16 | 1-12 | 1-9 | 1-7 | 1-17 | 1-13 | |
| GIRA | 0307 00/102 | 20-525W | 1-14 | | 1-14 | 1-10 | | 1-6 | 1-15 | 1-11 | 1-11 |
| JUNG | 225 NV DE | 20-500W/LED3-100W | 1-13 | 1-3 | 1-13 | 1-10 | 1-7 | 1-6 | 1-14 | 1-11 | |
| JUNG | 266 G DE | 60-600W | 1-16 | 1-3 | 1-16 | 1-12 | 1-9 | 1-7 | 1-7 | 1-13 | |
| Klemko | 891040 | 315W | | 1-5 | | | | | 1-6 | 1-6 | |
| Legrand | 617 030 | 40-600w | 1-16 | | | 1-12 | | 1-7 | | 1-13 | |
| merten | MEG5134-0000 | 4-400W | 1-10 | 1-10 | 1-11 | 1-8 | 1-6 | 1-5 | 1-11 | 1-11 | 1-13 |
| NIKO | 310-0190X | 5-325W | 1-8 | 1-13 | 1-9 | 1-6 | 1-4 | 1-4 | 1-9 | 1-7 | 1-13 |
| NIKO | 310-02900 | 3-300W | 1-8 | | 1-8 | 1-6 | 1-4 | 1-3 | 1-8 | 1-7 | |
| NIKO | 310-0490X | 4-200W | 1-6 | 1-5 | 1-6 | 1-6 | 1-3 | 1-3 | 1-6 | 1-5 | |
| NIKO | 310-0390X | 3-200W | 1-5 | 1-5 | 1-5 | 1-5 | 1-3 | 1-2 | 1-5 | 1-5 | |
| NIKO | 310-0280X | 2-100W | 1-3 | 1-12 | 1-2 | 1-3 | 1-7 | 1 | 1-3 | 1-11 | 1-7 |
| NVC | EP8D11A BLB5 | 400W | 1-10 | 1-9 | 1-11 | 1-8 | 1-6 | 1-5 | 1-11 | | 1-11 |
| OPUS | 852,397 | 7-110W/LED3-35W | 1-4 | 1-4 | 1-4 | 1-3 | 1-2 | 1-2 | 1-5 | 1-3 | 1-2 |
| PEHA | TRONIC-DIMMER 435 HAB | 20-600W | 1-16 | 1-10 | 1-16 | 1-12 | 1-7 | 1-7 | 1-17 | 1-2 | 1-8 |
| PEHA | D 431HAN LED | 6-120W/LED6-60W | 1-8 | 1-7 | 1-8 | 1-6 | 1-4 | 1-4 | 1-8 | 1-7 | 1-7 |
| TRUMP | DIMMAX 420SL | 400W | | 1-10 | | | | | | | |
| Panasonic | B5 EN 60669-2-1 | 150-500W | | | | 1-10 | 1-7 | 1-6 | | | 1-11 |
| Panasonic | WEG578153 | 80-500W | 1-13 | | 1-13 | 1-10 | 1-7 | 1-6 | 1-14 | 1-11 | 1-11 |
| SIEMENS | 5UH8222-3NC01 | 40-500W | 1-13 | 1-11 | 1-13 | 1-10 | 1-7 | 1-6 | 1-14 | | 1-13 |

Please note: For example, a Berker 286610 dimmer can control a minimum of 1 and a maximum of 10 Oppl GU10 3.2W lamps

Appendix

Version Oktober 2020
Änderungen vorbehalten
148





| Dimmer brand | Model | Type | Max. load | Filament | | | | | | | | | | | | |
|--------------|----------------------------|------------|----------------|---|---|---|---|--|---|---|---|---|---|---|---|------|
| | | | | A60 | A60 | G45 | G45 | P45 | P45 | B35 | B35 | ST64 | ST64 | ST64 | ST64 | |
| | | | | 470lm | 806lm | 250lm | 470lm | 250lm | 470lm | 250lm | 470lm | 470lm | 806lm | 400lm | 700lm | |
| | | | |  |  |  |  |  |  |  |  |  |  |  |  | |
| Berker | 286610 | RL | 500W | 1-20 | 1-20 | 2-10 | 1-20 | 2-10 | 1-20 | 2-10 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Berker | 2819 | R | 400W | 1-20 | 1-20 | 1-20 | 1-20 | | 1-20 | | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Berker | 283010 | R | 400W | 1-20 | 1-20 | 1-12 | 1-20 | 1-12 | 1-20 | 1-12 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Bticino | N4411N | | 400W/75W (LED) | 1-20 | 1-10 | 1-16 | 1-20 | 2-20 | 1-20 | 2-20 | 1-20 | 1-20 | 1-10 | 1-20 | 1-10 | 1-10 |
| Busch Jaeger | 2247U | RL | 500W | 1-20 | 1-20 | 2-20 | 1-20 | 2-20 | 1-20 | 2-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Busch Jaeger | 2250U | R | 600W | 1-20 | 1-20 | 1-12 | 1-20 | 1-12 | 1-20 | 1-12 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Busch Jaeger | 6513 U-102 | RC | 40-420W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Busch Jaeger | 6523U | R,L | 100W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Busch Jaeger | 6523 U-102 | R,C | 250W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Busch Jaeger | 6591 U-101-500 | | 60-420W | 1-20 | 1-18 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-18 | 1-20 | 1-18 | 1-18 |
| Busch Jaeger | 6523 UR-103 | | 2-400W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Druck | 8095 | RL | 400W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| EFAPEL | 21212 | | 250W/85W (LED) | 1-18 | 1-12 | 1-20 | 1-18 | | 1-20 | | 1-20 | 1-18 | 1-12 | 1-18 | 1-12 | 1-12 |
| EFAPEL | 21214 | | 110W/35W (LED) | 1-7 | 1-5 | 1-7 | 1-7 | 1-12 | 1-12 | 1-12 | 1-12 | 1-7 | 1-5 | 1-7 | 1-5 | 1-5 |
| EFAPEL | 21215 | | 150W/50W (LED) | 2-11 | 4-7 | | 2-11 | | 1-17 | | 1-17 | 2-11 | 4-7 | 2-11 | 4-7 | 4-7 |
| EFAPEL | 21216 | | 5-150W (LED) | | | | | 1-20 | 1-10 | 1-20 | 1-10 | | | | | |
| EPV | PAB 315 | | 315W | 1-20 | 2-12 | 2-20 | 1-20 | | 1-20 | | 1-20 | 1-20 | 2-12 | 1-20 | 2-12 | 2-12 |
| Feller | 40200 LED FMI 61 | | 400W | 1-20 | 1-16 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-16 | 1-20 | 1-16 | 1-16 |
| Feller | 40600 RL FIM61 | | 40-600W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Feller | 40300 RC FMI 61 | | 20-300W | 1-20 | 1-16 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-16 | 1-20 | 1-16 | 1-16 |
| Feller | 40600 RLC FMI 61 | | 20-600W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Gira | 1176 00/104 | R,L,C | 420W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Gira | 2262 00/101 | R,L | 500W | 1-20 | 1-20 | 2-20 | 1-20 | 2-20 | 1-20 | 2-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Gira | 030200 | R | 600W | 1-20 | 1-20 | 1-12 | 1-20 | | | | | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Gira | 030700 | R,C | 525W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Jung | 266 GDE | R | 60-600W | | 1-20 | 1-20 | | 1-20 | | 1-20 | | | 1-20 | | 1-20 | 1-20 |
| Jung | Licht-Management 225 NV DE | RL | 100W | 1-20 | 1-20 | 2-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Legrand | 617 030 | | 40-600W | 6-20 | 7-20 | 4-20 | 6-20 | 4-20 | 1-20 | 4-20 | 1-20 | 6-20 | 7-20 | 6-20 | 7-20 | 7-20 |
| Legrand | 665714 | | 400W/75W (LED) | 1-20 | 1-10 | 1-16 | 1-20 | 2-20 | 1-20 | 2-20 | 1-20 | 1-20 | 1-10 | 1-20 | 1-10 | 1-10 |
| merten | MEG5134-0000 | | 4-400W | 2-20 | 2-16 | 2-20 | 2-20 | 1-20 | 1-20 | 1-20 | 1-20 | 2-20 | 2-16 | 2-20 | 2-16 | 2-16 |
| NIKO | 310-02900 | | 200W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| NIKO | 310-01901 | R,L,C,CFli | 325W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| NIKO | 310-0490X | | 4-200W | 1-12 | 1-8 | 1-20 | 1-12 | 1-20 | 1-12 | 1-20 | 1-12 | 1-12 | 1-8 | 1-12 | 1-8 | 1-8 |
| NIKO | 310-0280X | | 2-100W | 1-6 | 1-4 | 1-12 | 1-6 | 1-12 | 1-6 | 1-12 | 1-6 | 1-6 | 1-4 | 1-6 | 1-6 | 1-4 |
| NVC | EP8D11A BLB5 | | 400W | 4-20 | 2-20 | 4-20 | 4-20 | 4-20 | 1-20 | 4-20 | 1-20 | 4-20 | 2-20 | 4-20 | 4-20 | 2-20 |
| PEHA | 431 HAN LED | | 120W/60W (LED) | 1-13 | 1-8 | 1-13 | 1-13 | 1-20 | 1-20 | 1-20 | 1-20 | 1-13 | 1-8 | 1-13 | 1-8 | 1-8 |
| PEHA | 435 HAB | | 20-525W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Panasonic | BS EN 60669-2-1 | | 150W-500W | 1-4 | 5-12 | | 1-4 | 3-8 | 1-8 | 3-8 | 1-8 | 1-4 | 5-12 | 1-4 | 5-12 | 5-12 |
| Panasonic | WEG578153 | | 80-500W | 1-20 | 4-20 | | 1-20 | 3-9 | 1-9 | 3-9 | 1-9 | 1-20 | 4-20 | 1-20 | 4-20 | 4-20 |
| SIEMENS | 5UH8222-3NC01 | | 40W-500W | 1-20 | 1-20 | 1-20 | 1-20 | 3-20 | 1-20 | 3-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Wintop | 13212 | L | 300W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |
| Wintop | 13512 | RC | 500W | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 | 1-20 |

Kompatibilitätsliste Dimmer

Kompatibel: kein Flackern,
keine Geräusche

Semi-kompatibel: kein
Flackern, ggf. Geräusche

Inkompatibel: ggf.
Flackern, ggf. Geräusche

| Dimmer brand | Model | Type | Max. load | GU10 | | | LED Module Clio GEN2 | | LED Ceiling Light Apollo | T5 Batten DIM | |
|--------------|-------------------------------|------------|---------------|---|------|------|---|-----|---|---|------|
| | | | | 3,2W | 5,2W | 7,5W | 22W | 36W | 22W | 9W | 18W |
| | | | |  | | |  | |  |  | |
| Berker | 286610 | RL | 500W | 1-10 | 1-3 | | 1-4 | 1-3 | 1-4 | 1-6 | 1-3 |
| Berker | 2819 | R | 400W | 1-7 | 1-4 | | 1-1 | 1-1 | 1-1 | 1-3 | 1-3 |
| Berker | 283010 | R | 400W | 1-10 | 1-3 | 1-10 | 1-2 | 1-1 | 1-2 | 1-3 | 1-3 |
| Busch Jaeger | 2247U | RL | 500W | 1-10 | 1-3 | 1-10 | 1-4 | 1-3 | 1-4 | 1-6 | 1-6 |
| Busch Jaeger | 2250U | R | 600W | 1-10 | 1-5 | 1-10 | 1-5 | 1-3 | 1-5 | 1-6 | 1-5 |
| Busch Jaeger | 6513 U-102 | RC | 40-420W | 2-10 | 1-10 | 1-10 | 1-6 | 1-4 | 1-6 | 1-9 | 1-5 |
| Busch Jaeger | 6523U | R,L | 100W | 1-10 | 1-5 | 1-10 | 1-1 | 1-2 | 1-1 | 1-1 | 1-1 |
| Busch Jaeger | 6523 U-102 | R,C | 250W | 1-10 | 1-10 | 1-10 | 1-1 | 1-1 | 1-1 | 1-1 | 1-1 |
| Bticino | N4411N | | 400W/75W(LED) | 1-20 | 1-14 | 1-10 | 1-3 | 1-2 | 1-3 | | |
| BULL | B6GD100 | | 200W | | | | | | | | |
| Druck | 8095 | RL | 400W | 1-10 | 1-10 | 1-10 | 1-2 | 1-2 | 1-2 | 1-3 | 1-3 |
| EFAPEL | 21212 | | 250W/85W(LED) | 1-20 | | | 1-1 | 1-1 | 1-1 | | |
| EFAPEL | 21214 | | 110W/35W(LED) | 1-10 | | | | | | | |
| EFAPEL | 21215 | | 150W/50W(LED) | | | | 1-2 | | 1-2 | | |
| EFAPEL | 21216 | | 5-150W(LED) | | | | | | | | |
| EPV | PAB 315 | | 315W | 1-8 | 1-13 | 1-11 | | | | | |
| Feller | 40200 LED FMI 61 | | 400W | 1-11 | 1-17 | 1-14 | 1-5 | 1-3 | 1-5 | | |
| Feller | 40600 RL FIM61 | | 40-600W | 1-5 | 1-7 | 1-9 | 1-4 | 1-2 | 1-4 | | |
| Feller | 40300 RC FMI 61 | | 20-300W | 1-11 | 1-17 | 1-14 | 1-5 | 1-3 | 1-5 | | |
| Feller | 40600 RLC FMI 61 | | 20-600W | 1-8 | 1-7 | 1-9 | 1-4 | 1-3 | 1-4 | | |
| Gira | 1176 00/104 | R,L,C | 420W | 1-10 | 1-10 | 1-10 | 1-2 | 1-2 | 1-2 | 1-18 | 1-12 |
| Gira | 2262 00/101 | R,L | 500W | 1-10 | 1-10 | 1-10 | 1-5 | 1-3 | 1-5 | 1-6 | 1-6 |
| Gira | 030200 | R | 600W | 1-10 | 1-3 | 1-10 | 1-5 | 1-3 | 1-5 | 1-6 | 1-6 |
| Gira | 030700 | R,C | 525W | 1-10 | 1-10 | 1-10 | 1-5 | 1-4 | 1-5 | 1-23 | 1-16 |
| Jung | 266 GDE | R | 60-600W | 1-10 | 1-7 | 1-10 | 1-4 | 1-3 | 1-4 | 1-6 | 1-6 |
| Jung | Licht-Management 225 NV DE | RL | 100W | 1-10 | 1-5 | 1-10 | | | | 1-6 | 1-6 |
| Legrand | 617 030 | | 40-600W | 2-7 | | | 1-2 | | 1-2 | | |
| Legrand | 665714 | | 400W/75W(LED) | 1-20 | 1-14 | 1-10 | 1-3 | 1-2 | 1-3 | | |
| merten | MEG5134-0000 | | 4-400W | 1-11 | 1-17 | 1-20 | 1-5 | 1-3 | 1-5 | | |
| NIKO | 310-01901 | R,L,C,CFLi | 325W | 1-8 | 1-13 | 1-8 | 1-4 | 1-3 | 1-4 | 1-13 | 1-9 |
| NIKO | 310-0190X | | 5-325W | 1-8 | 1-13 | 1-10 | 1-4 | 1-3 | 1-4 | | |
| NVC | EP8D11A BLB5 | | 400W | 1-2 | 1-2 | 1-2 | 1-1 | 1-1 | 1-1 | | |
| NIKO | 310-02900 | | 200W | 1-2 | 1-2 | 1-2 | 1-1 | 1-1 | 1-1 | | |
| OPUS | 852,397 | | 110W/35W(LED) | 1-10 | 1-6 | 1-4 | | | | | |
| PEHA | 431 HAN LED | | 120W/60W(LED) | 1-13 | 1-11 | 1-7 | 1-2 | | 1-2 | | |
| PEHA | 435 HAB | | 20-525W | 1-14 | 1-20 | 1-20 | 1-5 | 1-5 | 1-5 | | |
| Panasonic | BS EN 60669-2-1 | | 150W-500W | 1-4 | 1-3 | 1-4 | 1-1 | 1-1 | 1-1 | | |
| Panasonic | WEG578153 | | 80-500W | 1-4 | 1-2 | | 1-2 | 1-1 | 1-2 | | |
| SIEMENS | 5UH8222-3NC01 | | 40W-500W | 1-5 | | 1-4 | 1-1 | 1-1 | 1-1 | | |
| Wintop | 13212 | L | 300W | | | | 1-2 | 1-1 | 1-2 | 1-2 | 1-2 |
| Wintop | 13512 | RC | 500W | 1-10 | 1-10 | 1-10 | 1-7 | 1-4 | 1-7 | 1-22 | 1-16 |

Appendix

Version Oktober 2020
Änderungen vorbehalten
150